

## FAST RECOVERY RECTIFIER DIODES

- VERY FAST RECOVERY TIME
- VERY LOW FORWARD RECOVERY TIME
- VERY LOW RECOVERED CHARGE



DO 4  
(Metal)

### APPLICATIONS

- DC AND AC MOTOR CONTROL
- SWITCHMODE POWER SUPPLY
- HIGH FREQUENCY CHOPPERS

### ABSOLUTE RATINGS (limiting values)

| Symbol             | Parameter                              |                            | Value       | Unit       |
|--------------------|----------------------------------------|----------------------------|-------------|------------|
| $I_{FRM}$          | Repetitive Peak Forward Current        | $t_p \leq 20\mu s$         | 130         | A          |
| $I_{F(AV)}$        | Average Forward Current                | $T_C = 100^\circ C$        | 12          | A          |
| $I_{FSM}$          | Surge non Repetitive Forward Current   | $t_p = 10ms$<br>Sinusoidal | 150         | A          |
| $P_{tot}$          | Power Dissipation                      | $T_C = 100^\circ C$        | 20          | W          |
| $T_{stg}$<br>$T_J$ | Storage and Junction Temperature Range |                            | - 65 to 150 | $^\circ C$ |

| Symbol    | Parameter                       | BYX61- |     |     |     |     | Unit |
|-----------|---------------------------------|--------|-----|-----|-----|-----|------|
|           |                                 | 50     | 100 | 200 | 300 | 400 |      |
| $V_{RRM}$ | Repetitive Peak Reverse Voltage | 50     | 100 | 200 | 300 | 400 | V    |

### THERMAL RESISTANCE

| Symbol        | Parameter     | Value | Unit         |
|---------------|---------------|-------|--------------|
| $R_{th(j-c)}$ | Junction-case | 2.5   | $^\circ C/W$ |

# ELECTRICAL CHARACTERISTICS

## STATIC CHARACTERISTICS

| Symbol | Test Conditions                               | Min. | Typ. | Max. | Unit |
|--------|-----------------------------------------------|------|------|------|------|
| $I_R$  | $T_J = 100^{\circ}\text{C}$ $V_R = V_{RRM}$   |      |      | 3    | mA   |
| $V_F$  | $T_J = 25^{\circ}\text{C}$ $I_F = 12\text{A}$ |      |      | 1.5  | V    |

## RECOVERY CHARACTERISTICS

| Symbol   | Test Conditions                                                                                        | Min. | Typ. | Max.  | Unit          |
|----------|--------------------------------------------------------------------------------------------------------|------|------|-------|---------------|
| $t_{rr}$ | $T_J = 25^{\circ}\text{C}$ $I_F = 1\text{A}$ $di_F/dt = -15\text{A}/\mu\text{s}$<br>$V_R = 30\text{V}$ |      |      | 100   | ns            |
| $Q_{rr}$ | $T_J = 25^{\circ}\text{C}$ $I_F = 1\text{A}$ $di_F/dt = -15\text{A}/\mu\text{s}$<br>$V_R = 30\text{V}$ |      |      | 0.075 | $\mu\text{C}$ |
| $I_{RM}$ | $T_J = 25^{\circ}\text{C}$ $I_F = 1\text{A}$ $di_F/dt = -15\text{A}/\mu\text{s}$<br>$V_R = 30\text{V}$ |      |      | 1.5   | A             |

To evaluate the conduction losses use the following equations :

$$V_F = 1.15 + 0.015 I_F \qquad P = 1.5 \times I_{F(AV)} + 0.015 I_F^2 (RMS)$$