

2 SD 1890	Si-N-Darl	NF/S-L, 100V, 3A, 35W, 20MHz, B>5000	17c	(2SD1415)	17c	13
2 SD 1891	Si-N-Darl	NF/S-L, 110V, 4A, 40W, 20MHz, B>5000	17c	-		
2 SD 1892	Si-N-Darl	NF/S-L, 120V, 5A, 45W, 20MHz, B>5000	17c	-		
2 SD 1893	Si-N-Darl	NF/S-L, 130V, 6A, 50W, 20MHz, B>5000	16c	-		
2 SD 1894	Si-N-Darl	NF/S-L, 160V, 7A, 70W, 20MHz, B>5000	16c	-		
2 SD 1895	Si-N-Darl	NF/S-L, 160V, 8A, 100W, 20MHz, B>5000	16c	-		
2 SD 1896	Si-N	NF/S-L, 100V, 5A, 40W, 8MHz	17j	BD 243 C	17j	
2 SD 1897	Si-N	=2SD1896: Iso, 30W	17c	2SD1411	17c	
2 SD 1899(-Z)	Si-N	NF/S-L, 60V, 3A, 10W, 120MHz	30j	2SC3303	30j	
2 SD 1900	Si-N-Darl	NF/S-L, 60V, 4A, 25W, B=5000	15c	2SD1415	17c	
2 SD 1901	Si-N-Darl	NF/S-L, 60V, 8A, 25W, B=5000	15c	2SD1415	17c	
2 SD 1902	Si-N	NF-L, 60V, 3A, 30W, 40MHz	30j	(BD 243 C)	17j	6
2 SD 1903	Si-N	S-L, lo-sat, 60V, 8A, 30W, 120MHz	30j	(2SD1062)	17j	6
2 SD 1904	Si-N	S-L, lo-sat, 60V, 5A, 30W, 30MHz	30j	(2SD1062)	17j	6
2 SD 1905	Si-N	S-L, lo-sat, 60V, 7A, 40W, 10MHz	30j	(2SD1062)	17j	6
2 SD 1906	Si-N	S-L, lo-sat, 90V, 5A, 30W, 20MHz	30j	-		
2 SD 1907	Si-N	S-L, lo-sat, 90V, 7A, 40W, 20MHz	30j	-		
2 SD 1908	Si-N	TV-HA, 330/150V, 7A, 50W, 40MHz	30j	(BU 406)	17j	6
2 SD 1909	Si-N-Darl	NF/S-L, 500/300V, 6A, 45W, B>500	17c	2SD1409	17c	
2 SD 1910	Si-N+Di	TV-HA, 1500/600V, 3A, 40W	≈18c	2SD1555	18c	
2 SD 1910 FI	Si-N+Di	=2SD1910:	18c	→2SD1910		
2 SD 1911	Si-N+Di	TV-HA, 1500/600V, 5A, 50W	≈18c	BU 2508 DF	16c	
2 SD 1912	Si-N	NF-L, 60V, 3A, 30W, 100MHz	17j	2SC3258	17j	
2 SD 1913	Si-N	=2SD1912: Iso, 20W	17c	2SD1913	17c	
2 SD 1914	Si-N-Darl+Di	Tr-L, 100V, 2A, 10W, B=2k...30k	≈14h	-		
2 SD 1915	Si-N	hi-Ueb(25V), hi-beta, 50V, 0,3A, B>500	40c	(2SC3225)	7c(9mm)	
2 SD 1916	Si-N-Darl+Di	Uni, 50V, 2A, 1W, B=5000	9c	2SD1153	7c(9mm)	
2 SD 1917	Si-N-Darl	int. Z-Di(B →C), 60V, 1A, B=20000	14b	-		
2 SD 1918(F5)	Si-N	NF/S-L, 160/160V, 1,5A, 10W, 80MHz	30j	-		
2 SD 1919	Si-N	=2SD1055: Pins = 14mm	9c	→2SD1055		
2 SD 1920	Si-N	=2SD1469: Pins = 14mm	9c	→2SD1469		
2 SD 1921	Si-N	=2SD1787: Pins = 14mm	9c	→2SD1787		
2 SD 1922	Si-N+Di	int.Z-Di(B→C), 25V, 0,8A, 0,9W, B=600	7c(9mm)	-		
2 SD 1923	Si-N-Darl+Di	NF/S-L, 80V, 4A, 25W, B=5000	15c	2SD1415	17c	
2 SD 1924	Si-N-Darl+Di	NF/S-L, 80V, 8A, 25W, B=5000	15c	2SD1415	17c	
2 SD 1925	Si-N-Darl+Di	NF/S-L, 120V, 3A, 25W, B=5000	15c	-		
2 SD 1926	Si-N-Darl	NF/S-L, 200/200V, 10A, 30W, B=5000	15c	-		
2 SD 1927	Si-N-Darl+Di	NF/S-L, 120/120V, 6A, 25W, B=5000	15c	-		
2 SD 1928	Si-N-Darl+Di	S-L, 100/100V, ±8A, 25W, B>2000	17c	2SD1415	17c	
2 SD 1929	Si-N-Darl+Di	int. Z-Di(B →C), 60V, 2A, 1,2W, B=5000	7c(9mm)	2SD1153	7c(9mm)	
2 SD 1930	Si-N-Darl	Uni, 100V, 2A, 1,2W, B=5000	7c(9mm)	-		
2 SD 1931	Si-N-Darl+Di	int.Z-Di(B→C), 60V, 2A, 1,2W, B=10000	7c(9mm)	-		
2 SD 1932	Si-N-Darl+Di	NF/S-L, 80/80V, 4A, 35W, B=3000	17j	BD 901	17j	
2 SD 1933	Si-N-Darl+Di	=2SD1932: Iso, 30W	17c	2SD1415	17c	
2 SD 1934	Si-N	=2SD965: 1W	7c(9mm)	2SD2179	9c	
2 SD 1936	Si-N	NF, lo-sat, 15V, 0,8A, 0,3W, 200MHz	40c	2SD1207	7c	
2 SD 1937	Si-N	=2SD1211:	7c(9mm)	2SD1812	7c(9mm)	
2 SD 1939	Si-N-Darl+Di	S, 150/60V, ±1,5A, 0,75W, B>2000	7c	-		
2 SD 1940	Si-N	NF/S-L, 100V, 6A, 25W, 15MHz	17c	2SD1411	17c	
2 SD 1941	Si-N	TV-HA, 1500/650V, 6A, 50W	≈18c	BU 2508 AF	16c	
2 SD 1942	Si-N	NF, 40V, 2A, 1,2W	7c(9mm)	2SD1207	7c(9mm)	
2 SD 1943	Si-N	hi-beta, 80V, 3A, 40W, 50MHz, B>400	17j	(2SD1273)	17c	
2 SD 1944	Si-N	=2SD1943: Iso, 30W	17c	2SD1273	17c	
2 SD 1945	Si-N	NF/S-L, 1000/1000V, 0,5A, 20W	30j	-		
2 SD 1947(A)	Si-N+Di	hi-beta, lo-sat, 100V, 10A, 70MHz, B>500	17c	-		
2 SD 1948	Si-N+Di	hi-beta, lo-sat, 60V, 5A, 110MHz, B>500	17c	-		